



Product Data Sheet

No. 69720 - 03/13

PORTABLE AREA LIGHTS

#9720 - PORTABEL AREA LIGHT

#9721 - PORTABLE AREA LIGHT SET (3-LIGHTS)



#9721 3-Pack Set



#9720 Single Light

Sierra Wave™ Portable Area Lights operate off of 12V DC power which is provided from any Sierra Wave Power Center or other 12V DC power receptacle. Hang above a work surface or living/work area for portable light where needed. Up to 10 lights may be chained together to increase light span. Each light contains 88 super-bright LEDs and provide 400 lumens.

SPECIFICATIONS

Each Area Light Contains

LED Bulb	3W, 66 LED, 30,000 hours.
Light Brightness.....	400 Lumens
DC Input.....	12V DC
12V DC Adapter.....	12/24V DC
Fuse	Replace with 2A/250V DC glass fuse (spares are included)
Operating Temperature.....	32°F - 120°F
Weight.....	8 oz.
Dimensions.....	Light Globe: 5.5" x 4"
Power Cord Length	10 ft.

Packaging:

#9720 Each box:	1 lbs. (0.5 kg)	0.12 CF (0.003 CM)	5.5" L x 5.5" W x 6.75" H
#9720 Case (4/case):	5 lbs. (2.3 kg)	0.625 CF (0.02 CM)	12" L x 12" W x 7.5" H
#9721 Each box:	3 lbs (1.4 kg)	0.29 CF (0.008 CM)	13.375" L x 5.5" W x 6.75" H
#9721 Case (2/case):	6 lbs. (2.7 kg)	0.72 CF (0.02 CM)	13.75" H x 12" W x 7.5" H



AerVOE Industries, Inc.
P.O. Box 485, Gardnerville, NV 89410

(775) 783-3100 Phone • (775) 782-5687 Fax • (800) 227-0196 Customer Service
www.aerVOE.com • mailbox@aerVOE.com

PARTS IDENTIFICATION (each light contains)



OPERATING INFORMATION

The Sierra Wave Portable Area Lights bring light to unlit areas, whether permanent or temporary. Hang them on a tree branch, string line, or any other overhead structure using the carabiner clip that is attached to each unit. Then connect to any 12V DC power source. Ideal for emergency preparedness but also for un-powered work sights, camping, boating, and patios. To increase lit area, attach additional Portable Area Lights (#9720 singles or #9721 sets), up to 10 lights. Unplug from power source before connecting additional lights.

Operation Time

(from a fully charged power center)

#9670 Solar Link 240 Power Center	1 light, 60–75 hours 3 lights, 20–25 hours
#9675 Solar Link 1000 Power Center	1 light, 250–300 hours 3 lights, 80–100 hours
#6994 Power Center ¹⁰⁰	1 light, 30–33 hours 3 lights, 10–12 hours
#9660 60–Watt Power Cell	1 light, 15–20 hours 3 lights, 5–6 hours
Vehicle Power Supply (engine running)	Unlimited

Available Medium to Large Storage Devices



9670 Sierra Wave™ Solar Link 240



9675 Sierra Wave™ Solar Link 1000



9660 Sierra Wave™ 60–Watt Power Cell



6994 Max Burton Power Center¹⁰⁰

WARRANTY

1-year performance warranty on all products from date of purchase. Report to home office or local Aervoe representative for examination. Because Seller cannot control Buyer's handling or use of product, Seller makes no warranty expressed or implied when not used or stored in accordance with directions. Seller shall not be liable for cost of labor, incidental or consequential damages, and this warranty is limited to repair or replacement of product at company option.